

Override Outbound on Listening IP

THE INFORMATION IN THIS ARTICLE APPLIES TO:

- EFT Server version 5.2.12 and later

DISCUSSION

In EFT Server 5.2.11 and earlier, if an outbound event was scheduled, EFT Server would use the first IP address in the system's IP address list rather than the listening IP address for the Site. This behavior was changed in EFT Server 5.2.12 so that EFT Server now uses the listening IP address. In recognition that this could adversely affect some of our customers, we added a registry setting to revert to the old behavior.

To return to the legacy behavior, create the following key:

On 32-bit systems:

```
[HKEY_LOCAL_MACHINE\SOFTWARE\GlobalSCAPE Inc.\EFT Server 4.0]
```

On 64-bit systems:

```
[HKEY_LOCAL_MACHINE\Software\Wow6432Node\GlobalSCAPE Inc.\EFT Server 4.0]
```

```
"LegacyListenIP"=dword:00000001
```

1 to enable, 0 or does not exist (default) to disable

GlobalSCAPE Knowledge Base

<https://kb.globalscape.com/Knowledgebase/10485/Override-Outbound-on-Listeni...>